

Wright Audio

Oasis Music System

PH-2 Phono Stage

The Wright Audio PH-2 allows the Wright Audio Integrated Amplifiers and Line Preamplifiers to accept the output from a turntable. It may also be used with other manufacturers' products.

- Sensitivity: 2.0 mv into Wright Audio components.
- For standard moving magnet or high output moving coil phono cartridges requiring 47K ohm input impedance.
- Drives input impedance of 30K or higher.
- Unit does not invert phase.
- Tube complement: (3) 12AX7 / ECC83.

SAFETY WARNINGS

1. Do not open the cover of the preamplifier. Lethal voltages may exist within, **even when the power cord is disconnected from the outlet**. It should be returned to Wright Audio if there is a malfunction.
2. The unit must not be exposed to excessive moisture. Never use any more than a cloth **lightly** moistened with water for cleaning.
3. Be sure to turn off the power supply before unplugging the PH-2 from the power supply. After the power supply has been turned off, wait a couple minutes before unplugging the PH-2 from the power supply to allow most of the high voltage to dissipate. Be sure the power switch is OFF on the PH-2 before connecting or disconnecting it from the power supply.

INSTALLATION and OPERATION

1. Locate the preamplifier where there is adequate ventilation -- at least 2 inches above it.
2. The tubes have already been installed. The metal shields for the tubes are used to reduce hum from stray electrical fields. If you do not experience excessive noise by removing them during operation, it is best to leave them off.
3. Be sure the power supply is OFF before connecting **or disconnecting** the PH-2 from the power supply.
4. Connect the main left and right channel cables from the turntable to the INPUT left and right channel sockets. Also connect the single ground wire from the turntable to the GND screw and tighten.
5. Connect the PH-2's left and right outputs to the appropriate device.
6. After turning the power supply on, turn the switch on the PH-2 to the 'Mute' position. During normal operation, the 'Mute' position is useful when placing the needle on or off the record to prevent 'thumps' from the speaker.

The unit requires no maintenance other than tube replacement. The tubes should be replaced as a set every 3 or 4 years (normally about 4000 hours of operation). Although the tubes will still operate beyond this point, much of the 'tube magic' will diminish.

Wright Audio supplies the correct replacement tubes for your unit at reasonable cost.

It is unnecessary to operate your preamplifier when you are NOT listening. Unlike solid-state equipment, the preamplifier reaches its optimum listening quality in about 10 minutes, and it is simply a waste of power and tube life to leave it on continuously.

When the unit is new, it will require 2 or 3 days of operation approaching 2 hours per day before it 'breaks in' and begins to sound its best and will continue to improve over the next few weeks.

IF YOU HAVE A PROBLEM OR QUESTION

Your product was designed for a lifetime of operation with ordinary common sense care, and infrequent tube replacement. Please accord it with the same care as you would a fine camera. However, damage can occur during shipping or in storage conditions where extremes of temperature can render the unit faulty. Neither of these exposures may be visible to the eye.

Your continued satisfaction with our products is extremely important to us. We will be happy to answer your questions pertinent to the installation and operation of your unit. Please feel free to write, call or email in the event of any difficulty, and we shall endeavor to provide prompt service. If the problem cannot be resolved through our combined efforts, we may wish to authorize the return of your unit to us.

UNDER NO CIRCUMSTANCES SHOULD YOUR UNIT BE SHIPPED TO WRIGHT AUDIO WITHOUT AUTHORIZATION. An item sent to us under either of these conditions will be refused.

Ship **PREPAID** via **UPS** or **FEDERAL EXPRESS ONLY**. Be sure to insure the shipment for the full cost of the unit. **FREIGHT COLLECT** shipments cannot be accepted.

www.WrightAudio.us